

81 SERIES

Square Rear Lamps



Part#	Description	EAN Code
81A	Square Indicator Lamp, 12V, Blister Pack	9335962012817
81AM	Square Indicator Lamp, 12/24V, Blister Pack	9335962012879
81R	Square Stop / Tail Lamp, 12V, Blister Pack	9335962012824
81RM	Square Stop / Tail Lamp, 12/24V, Blister Pack	9335962012886
81F	Square Fog Lamp, 12V, Blister Pack	9335962012909
81FM	Square Fog Lamp, 12/24V, Blister Pack	9335962012800
81W	Square Reverse Lamp, 12V, Blister Pack	9335962012862
81WM	Square Reverse Lamp, 12/24V, Blister Pack	9335962012893
81STI	Square Stop / Tail / Indicator Lamp, 12V, Blister Pack	9335962012831
81STIM	Square Stop / Tail / Indicator Lamp, 12/24V, Blister Pack	9335962012848

Voltage	9-16V or 9-32V
Dimensions	81 x 81 x 24mm
IP rating	IP67
Warranty	5 Years
Cable	300mm (stripped-end)
Operating temperature	-30°C to +50°C
Current draw (13.8V / 28V)	Stop: 0.22A / 0.12A, Tail: 0.01A / 0.01A, Indicator: 0.19A / 0.11A, Fog: 0.17A / 0.11A, Reverse: 0.30A / 0.17A

ECE approval	Function	Single Function Approval#	Stop/Tail/Ind. Approval#
	Stop / Tail (R7)	R1-S1-E9-02.11053	R1-S1-E9-02.11054
	Indicator (R6)	2a-E9-01.6018	2a-E9-01.11054
	Reverse (R23)	AR-E9-00.1199	
	Fog (R38)	F1-E9-00.1038	

Wiring colour codes	BROWN: Tail [+] RED: Stop [+] BLACK: Reverse [+]	YELLOW: Indicator [+] BLUE: Fog [+] WHITE: Earth [-]
----------------------------	--	--

Mounting instructions	⚠ Installation to be undertaken by a competent professional 1. Drill bolt holes 51mm apart and drill a hole for the cable in between them. 2. Surface mount using the fixings provided.
------------------------------	--



81A / 81AM



81R / 81RM



81F / 81FM



81W / 81WM



81STI / 81STIM



81STIM Active

